

DIGITAL PRESSURE SENSOR

Series PS

Cat No PS - 01 - 01

Digital Pressure Sensor - 1/8

Features

- Set pressure selectable (Mpa, psi, kgf/cm2, bar)
- Both upper and lower limits of pressure can be set independently
- □ Panel mountable
- □ Direct mountable
- Both PNP & NPN versions
- □ Two outputs



Technical Specifications

Ordering no.		PS0101504 *	PS0102504 *
Port size		R 1/8	
Rated pressure range		0 ~ 10 bar	
Operating / Setting pressure range		-1 ~ 10 bar	
Withstand pressure		1.5 times of rated pressure range	
Fluid		Air	
	Мра	0.001	
Set pressure resolution	Kgf/cm ²	0.01	
	Bar	0.01	
	Psi	0.1	
Power supply voltage		12 to 24V DC ±10%, Ripple (P-P) 10% or less	
Current consumption		≤ 55 mA	
Switch output		NPN: open collector 2 outputs Max. load current: 80 mA Max. supply voltage: 30V DC Residual voltage: ≤ 1V (load current 80 mA)	PNP: open collector 2 outputs Max. load current: 80 mA Max. supply voltage: 24V DC Residual voltage: ≦ 1V (load current 80 mA)
Repeatability (Switch output)		≦ ±0.2% F.S. ± 1 digit	
Hysteresis	Hysteresis mode	Adjustable	
Window comparator mode		Fixed (3 digits)	
Response time		≤ 2.5ms (chattering-proof function: 24ms, 192ms and 768ms selections)	
Output short circuit protection		Yes	
7 segment LED display		3½ digit LED display (Sampling rate: 5 times/1sec.)	
Indicator accuracy		≤ ±2% F.S. ±1 digit (ambient temperature: 25 ±3°C)	
Indicator		Green LED (OUT1) Red LED (OUT2)	
Analog output		Output voltage: 1 to 5V ≦ ±2.5% FS (within rated pressure range) Linearity: ≦ ±1% F.S.	
Environment	Enclosure	IP40	
	Ambient temp. range	Operation: 0 ~ 50°C, Storage: -20 ~ 60°C (No condensation or freezing)	
	Ambient humidity range	Operation / Storage : 35 ~ 85% RH (No condensation)	
	Withstand voltage	1000VAC in 1-min (between case and lead wire)	
	Insulation resistance	50Mohm min. (at 500V DC M, between case and lead wire)	
	Vibration	Total amplitude 1.5mm, 10Hz-55Hz-10Hz scan for 1 minute, two hours each direction of X, Y and Z	
	Shock	980m/s² (100G), 3 times each in direction of X, Y and Z	
Temperature characteristic		≤ ±2% F.S. of detected pressure (25°C) at temp. Range of 0~50°C	
Lead wire		Oil-resistance cable (0.15mm²)	
Product weight		Approximate 105g (with 2-metre lead wire)	
Output circuit wiring graph		S DC(+) (Brown) 1KO Analog output OUT1 (Black) OUT2 (White) DC(-) (Blue)	DC(+) (Brown) 1KO Ansteg output (Orange) OUT1 (Black) OUT2 (White)

* Optional spare parts

A: Mounting bracket, B: Panel adapter, C: Panel adapter + Front protective lid




DIGITAL PRESSURE SENSOR


Series PS

Cat No PS - 01 - 01


Dimension / Panel instructions



1. Mounting Bracket



2. Panel type



How to Order

40

While ordering Digital pressure sensor, mention the ordering number given in the corresponding tables. Example: Pressure sensor NPN type with Panel adapter - PS0101504B

42.4

47.4